

# Fender Passport Event S2 PA System



Output power: 375 watts, class-D power amp

Channels: Seven (four XLR/ $\frac{1}{4}$ " combination Mic/Line, One Instrument/Line, Two Stereo with  $\frac{1}{4}$ ",  $\frac{1}{8}$ ", and Bluetooth® inputs)

Inputs: Nine (Four XLR  $\frac{1}{4}$ " combination mic/line, one  $\frac{1}{4}$ " instrument/line, two stereo  $\frac{1}{4}$ ", one stereo  $\frac{1}{8}$ ", stereo Bluetooth®)

Controls: Volume, treble, bass, reverb level and mic/line pad per channel, hi-Z instrument/line switch, Bluetooth® pair switch, master volume

Reverb effect

Speakers: Two 8" Fender Special Design speakers, two 1.2" horn-loaded tweeters

Other features: International voltage operation (100V-120V/220V-240V), seven-channel mixer, hi-Z  $\frac{1}{4}$ " input for instruments, stereo  $\frac{1}{8}$ " input, stereo  $\frac{1}{8}$ " output for headphone monitoring and sending stereo mixes, sub out with automatic high-pass filter for powered subwoofer use, mono output with level control for powered monitor use, 35mm (1-3/8") stand adapters built into each speaker cabinet, mic/cable storage compartment with latching lid



**Price:** \$839.99

***Customer Service Is Our Top Priority!***