

# Fender Passport Venue S2 PA System



Output Power: 600 watts, class-D power amp

Channels: Ten (four XLR mic/line, two  $\frac{1}{4}$ " line/hi-Z instrument, four stereo with  $\frac{1}{4}$ " and 1/8" inputs)

Inputs: 13 (four XLR mic/line, two  $\frac{1}{4}$ " instrument/line, four stereo  $\frac{1}{4}$ ", two stereo 1/8", one stereo Bluetooth®)

Controls: Volume, treble, bass and reverb on each channel, 20dB pad (channels 1-4), phantom power switch, reverb select, time and tone, hi-Z instrument/line switch, Bluetooth® pair switch, master volume, master tone

Reverb effect

Speaker: Two 10" Fender Special Design speakers, Two 1.2" horn-loaded tweeters

Other features: International voltage operation

(100V-120V/220V-240V), 10-channel mixer, stereo 1/8" input, stereo 1/8" output for headphone monitoring and sending stereo mixes, sub out with automatic high-pass filter for powered subwoofer use, mono output with level control for powered monitor use, 35mm (1-3/8") stand adapters built into each speaker cabinet, mic/cable storage compartment with latching lid



**Price:** \$1,399.99

**Customer Service Is Our Top Priority!**